

# THE BT DECT PORTFOLIO



## BT Freelance XD 8500



Colour: Titanium/Dark Grey

Type II Caller display  
 40 Number calls list  
 10 Number redial list  
 Directory: 50 Name & number

GAP compatible:	yes	Handsfree:	no		
Max. number of handsets:	5	Headset socket:	no		
Max. number of bases:	1	Auto answer:	yes		
Conference call:	yes	Secrecy:	yes	Call waiting indicator:	no
Call transfer:	yes	Handset naming:	yes	PBX access code:	no
Internal calls:	yes	Keypad lock:	yes	Repeater compatible:	no
Music on hold:	yes	Power on/off:	yes	Wall mount:	no
Indoor range* (Metres):	50	Inductive coupler:	no		
Outdoor range* (Metres):	300	Earpiece volume control:	yes	Talktime (hours):	12
		Handsfree volume control:	no	Standby (hours):	130
Display type:	mono	Call timer:	yes	Battery type:	NiMH
Display - number of lines #:	1	Clock:	yes	Battery size:	AAA
Backlit:	yes	Alarm:	yes	Battery capacity (mAh):	500
Contrast control:	no	Calendar:	no	Base PSU item code:	048611
		Appointments:	no	Charger PSU item code:	048610
		Illuminated keypad:	no		
		Keypad confirmation tone:	yes	<b>Recording machine</b>	
Handset polyphonic ringtones:	0	Low battery indicator:	yes	Recording time (mins):	up to 25
Handset standard ringtones:	5	Low battery alert:	yes	Playback:	handset & base
Handset ringer on/off:	yes	Out of range indicator:	yes	Outgoing messages:	4
Handset ringer volume control:	yes	Out of range alert:	yes	Recordable outgoing messages:	yes
Visual ring indicator:	yes	Handset settings PIN protected:	no	Answer delay:	yes
Associated ring tone:	yes	Belt clip:	no	Time saver:	yes
Base ringtones:	5			Remote access:	yes
Base ringer on/off:	yes			Message advice:	indicator & counter
Base ringer volume control:	yes			Call screening:	yes
		Base settings PIN protected:	no	Memo:	yes
		Find key on base:	yes	Audable message alert:	yes
SIM card:	no			Timed TAM:	yes
Caller groups:	no				

Notes:

\* In ideal conditions

# Including icons and soft keys, as appropriate

Technical support: Is available from the BT Helpdesk on Freephone 0800 218 2182 or via the email link on the product page at [www.bt.com/producthelp](http://www.bt.com/producthelp)

Status: Launched



# THE BT DECT PORTFOLIO

## BT Freelance XD 8500

### Weights and dimensions

Base (gms): 167  
Handset (gms): 94  
Charger (gms): 100

Base (cm): 4.8 x 13 x 10.7  
Handset (cm): 15 x 5.12 x 3.1  
Charger (cm): 4.8 x 11.6 x 9.42

### Giftbox - dimensions/complete/empty

1 Pack: 21 x 18 x 5.5 (cms) / 551 (gms) / 96 (gms)  
2 Pack: 21 x 18 x 9.5 (cms) / 926 (gms) / 128 (gms)  
3 Pack: 21 x 18 x 15.5 (cms) / 1403 (gms) / 191 (gms)  
4 Pack: 21 x 18 x 18.5 (cms) / 1760 (gms) / 209 (gms)  
Additional handset not available

### Overpack - dimensions/complete

1 Pack: 23.5 x 35 x 19.5 (cms) / 3638 (gms)  
2 Pack: 23.5 x 37.5 x 30.5 (cms) / 6032 (gms)  
3 Pack: 23.5 x 37.5 x 32.5 (cms) / 6078 (gms)  
4 Pack: 23.5 x 39 x 37.5 (cms) / 7631 (gms)  
Additional handset not available

### No. of giftboxes per overpack

1 Pack: 6  
2 Pack: 6  
3 Pack: 4  
4 Pack: 4  
Additional handset not available

### Pallet Ti's x Hi's

1 Pack: 15 x 5  
2 Pack: 9 x 5  
3 Pack: 8 x 5  
4 Pack: 8 x 5  
Additional handset not available

### Item code

1 Pack: 061925  
2 Pack: 061926  
3 Pack: 061927  
4 Pack: 061928  
Additional handset not available

### CSS code

1 Pack not available  
2 Pack not available  
3 Pack not available  
4 Pack not available  
Additional handset not available

### Barcode

1 Pack: 5016351614952  
2 Pack: 5016351614969  
3 Pack: 5016351614976  
4 Pack: 5016351614983  
Additional handset not available

### Overpack barcode

1 Pack: 05016351821077  
2 Pack: 05016351821084  
3 Pack: 05016351821091  
4 Pack: 05016351821107  
Additional handset not available

Country of manufacture: China